



Thanks for purchasing
this product!

boredbrain

MIND YOUR MUSIC

RICHMOND, VA | www.boredbrainmusic.com

Boredbrain INTRFX

The INTRFX facilitates effects processing between eurorack, guitar pedals and electronic instruments.

- 3 channels of send & return level conversion
- Per-channel selection of either eurorack thru pedals or instrument thru eurorack
- FX blend control with CV input
- Capable of FX feedback and linear VCA functionality
- Small tabletop form-factor

technical specs

- 6 x 1/4-in line-level jacks
- 6 x 3.5mm euro-level jacks
- 3 x 3.5mm control voltage inputs (10VPP)
- Power: 9VDC 75mA negative center 2.1mm
- Dimensions: 3.75 x 3.75 x 2.25 in
- Weight: 13.5 oz (383 g)

limited warranty

This product is guaranteed to be free of functional defects for a period of 180 days from original purchase date. Proof of purchase is required for any warranty claim. Return shipping costs are covered by Boredbrain Music within the first 30 days of purchase only. Products with obvious signs of abuse or that have been modified by the end user, may not be covered under this warranty, at the discretion of Boredbrain Music.

service & inquiries

If you experience a problem with your Boredbrain product, or just want to share something interesting with us, please contact us at the link below and be sure to include your name, original purchase date, and a description of the problem you are experiencing. Then just hold tight, as we return most inquiries within 48 hours. We want to work with you to resolve your issue as soon as possible. Thanks.

www.boredbrainmusic.com/contact



EURORACK FX INTERFACE

USER GUIDE

EURORACK THRU PEDALS



Switch to LEFT

Input & outputs on 3.5mm jacks

FX loop send & return on 1/4-in jacks

INSTRUMENT THRU EURORACK

Switch to RIGHT

Input & outputs on 1/4-in jacks

FX loop send & return on 3.5mm jacks

EURORACK I/O



3.5mm inputs & outputs
or sends & returns at
eurorack level

PEDALS & LINE I/O



1/4-in inputs & outputs
or sends & returns at
line level

HINT:

Eurorack I/O can also
be used with CV input
as a simple VCA for
audio and CV (inverted).

HINT:

Feedback effects can be
achieved by flipping
the Interchange Switch
into the "wrong" mode.

FX BLEND



Adjusts the mix between
the input and FX
return signal

INTERCHANGE SWITCH



Selects either Eurorack
thru Pedals or Instrument
thru Eurorack

CV INPUT



Automates the FX Blend using
control voltage signals (10VPP)

DC 9V

Power input: DC 9V 75mA, 2.1mm
(negative tip)

