

QUESTED Q212

Main System 3-Way Active Reference Monitor



The Q212 was the first "Quested" production monitor. It has been refined over the past 20 years, evolving into the current model.

The original Q212 system was installed at the innovative Rooster studios in London and is still in service. Newer systems include Trevor Horn's 5.1 set-up in SARM Studios London.

A three-way active system with remote electronics the Q212 is as appropriate as ever for the mid-sized control room needing superlative monitoring.

The monitors are supplied with a separate dedicated electronics package, 19" rack mounting power amplifiers and electronic crossover / loudspeaker management system.

Typical Applications: main monitors in mid-sized control rooms, components of multi-channel systems in large control rooms.

Size (WxHxD)	700(w) x 700(h) x 640(d) mm
Weight	80 kgs
Drivers	Bass cone: 2 x 305 mm (12") Midrange: 1 x 75mm (3") High Frequency 1 x 37mm (1.5")
Maximum SPL	126dB at 1m
Frequency Response	20Hz* - 20KHz +/- 2 dB
Input Connector	2 x twin-pair gold plated binding posts accept bare ends or 4mm banana plugs
Amplifier power	Bass 1550 W RMS into 4 Ohms Mid 475 W RMS into 8 Ohms High 475 W RMS into 8 Ohms
High Crossover Point	Linkwitz-Riley 4k5Hz, 24dB/oct
Low Crossover Point	Linkwitz-Riley 450Hz, 24dB/oct
Electronics (Pair)	Amplifier 2 x AP950-2 & 1 x AP1550-2
Crossover	1 x Quested SM748, 4-in/8-out Processor

*Low frequency response is dependent on room size/acoustics
All specifications subject to confirmation by Quested.



Custom Q212-n available for mounting as horizontal/vertical centre or surround alternatives.



Size
462 x 1104
x 610Q(d) mm

Quested Monitoring Systems

Unit 8, Kingsgate, Heathpark, Honiton, Devon EX14 1YG, UK - T +44 (0)1404 41500 - E info@quested.com

www.quested.com



EAT



SLEEP



MIX